


Better TV Signal Quality.

SQT783 Terrestrial Television Signal Meter



- ✓ Colour LCD Display
- ✓ Soft cover protects against drop damage
- ✓ Pre-programmed with Australian Channels
- ✓ Internal High Energy Lithium-Ion Battery 1800mAh
- ✓ High sensitivity assists searching for weak DTV signals
- ✓ Comprehensive digital TV measurements including Level, MER & BER

PRODUCT BENEFITS

- Spectrum display of signals
- Powers 5V DC mast amplifiers
- Reads weak and strong TV signals
- Instant response to signal changes
- Easy to use, compact handheld shape
- Audible Lock & Signal Quality Alarm
- Convenient LED Torch Light integrated
- Includes MER and BER signal readings
- Ready for DVB-T2, exceptional with DVB-T
- Magnetic Compass assists identifying direction
- Keypad LED Backlit assists use in dark corners
- Full Australian Channel plan pre-programmed
- Constellation diagram displays signals in an xy-plane scatter diagram

SPECIFICATIONS

Terrestrial Tuner & Demodulator	
FREQUENCY RANGE	50MHz to 858MHz
INPUT CONNECTOR	F Male, f-f adapter included for easy replacement
SIGNAL LEVEL RANGE	< 30 to 99dB μ V
ANTENNA LINE AMP POWER SUPPLY	5V @100mA maximum
CHANNEL BANDWIDTH	7 MHz default, 5, 6 or 8 Hw. ready



SQT783