



ANT1200A

FM band aerial complete with F connector. Different design for the **radio signals reception**.

| | | |
|---|--------|---------------|
| CODE | | 213001 |
| Elements | no. | 1 |
| Band | | FM |
| Bandwidth | MHz | 87.5-108 |
| Gain | dBi | 2.1 |
| Front/Back ratio | dB | Omni |
| Return loss | dB | -16 |
| Beamwidth (-3dB) | ° | 360 |
| Wind load at 120km/h (720N/m ²) | kg (N) | 3 (29.43) |
| Connector | Type | F |
| Impedance | Ω | 75 |
| Max mast (Ø) | mm | 60 |
| Dimensions (L x H) | cm | 96 x 77 |
| Quantity Masterbox | pcs | 10 |
| Unit weight | kg | 0.90 |
| Total weight | kg | 10.6 |
| Accessories | | |
| Horizontal polarization | | Included |

Horizontal polarization Tilt adjustment
Auxiliary boom

N.P.
N.P.

